

VX-130 Frequency Tables

CH	Frequency		VHF Color	MODEL	CHANNEL CH	CHART Frequency		CH	Frequency	
	(MHz)	BW				(MHz)	BW		(MHz)	BW
1	151.6250	W/N	Red		11	151.7450	W/N	21	154.6550	W/N
2	151.9550	W/N	Purple		12	151.7750	W/N	22	158.4000	W/N
3	154.5700	W/N	Blue		13	151.8650	W/N	-	-	-
4	154.6000	W/N	Green		14	151.8950	W/N	-	-	-
5	151.7000	W/N	-		15	151.9250	W/N	-	-	-
6	151.7600	W/N	-		16	152.7000	W/N	-	-	-
7	151.5125	W/N	-		17	154.4900	W/N	-	-	-
8	151.6550	W/N	-		18	154.5150	W/N	-	-	-
9	151.6850	W/N	-		19	154.5400	W/N	-	-	-
10	151.7150	W/N	-		20	154.6000	W/N	-	-	-

CH	Frequency		UHF Color	Model	CHANNEL CH	CHART Frequency		CH	Frequency		CH	Frequency		CH	Frequency		CH	Frequency	
	(MHz)	BW				(MHz)	BW		(MHz)	BW		(MHz)	BW		(MHz)	BW		(MHz)	BW
1	464.5000	W/N	Brown		11	461.0875	N	21	461.3375	N	31	464.5125	N	41	466.2125	N	51	467.8875	N
2	464.5500	W/N	Yellow		12	461.1125	N	22	461.3625	N	32	464.5375	N	42	466.2375	N	52	467.9125	N
3	467.7625	N	J		13	461.1375	N	23	462.7625	N	33	464.5625	N	43	466.2625	N	53	469.4875	N
4	467.8125	N	K		14	461.1625	N	24	462.7875	N	34	466.0375	N	44	466.2875	N	54	469.5125	N
5	467.8500	W/N	Silver Star		15	461.1875	N	25	462.8125	N	35	466.0625	N	45	466.3125	N	55	469.5375	N
6	467.8750	W/N	Gold Star		16	461.2125	N	26	462.8375	N	36	466.0875	N	46	466.3375	N	56	469.5625	N
7	467.9000	W/N	Red Star		17	461.2375	N	27	462.8625	N	37	466.1125	N	47	466.3625	N	-	-	-
8	467.9250	W/N	Blue Star		18	461.2625	N	28	462.8875	N	38	466.1375	N	48	467.7875	N	-	-	-
9	461.0375	N	-		19	461.2875	N	29	462.9125	N	39	466.1625	N	49	467.8375	N	-	-	-
10	461.0625	N	-		20	461.3125	N	30	464.4875	N	40	466.1875	N	50	467.8625	N	-	-	-